

NON SERIES 250VAC / 125VDC

Series	Ampere
Part Number	Range
NONxxx	125mA to 600A

Ampere Ratings: 125mA, 500mA, 750mA, 800mA, 1A, 1.25A, 1.5A, 1.6A, 2A, 2.5A, 3A, 3.2A, 4A, 5A, 6A, 6.25A, 7A, 8A, 9A, 10A, 12A, 15A, 20A, 25A, 30A, 35A, 40A, 45A, 50A, 60A, 65A, 70A, 75A, 80A, 90A, 100A, 110A, 125A, 150A, 175A, 200A, 225A, 250A, 300A, 350A, 400A, 450A, 500A, 600A

Sample P/N: NON005 for 5A fuse



I.R.: 50kA at 250VAC (Class K5 - 125mA to 60A)
 10kA at (Class H - 65A to 600A)
 50kA at 125VDC (Class K5 - 125mA to 60A)
 10kA at 125VDC (Class H - 65A to 100A)
Voltage: 250VAC (all) / 125VDC (125mA to 100A)
Pack Size (box): 10 (125mA to 60A)
 5 (65A to 100A)
 1 (110A to 600A)
Holders: Blocks for fuses up to 30A (p133)
 Blocks for fuses above 35A contact sales.
Fuse Classification: Fast Acting (One Time)
Approvals: UL, CE, CE

NOS SERIES 600VAC

Series	Ampere
Part Number	Range
NOSxxx	1A to 600A

Ampere Ratings: 1A, 2A, 3A, 4A, 5A, 6A, 7A, 8A, 9A, 10A, 12A, 15A, 20A, 25A, 30A, 35A, 40A, 45A, 50A, 60A, 70A, 75A, 80A, 90A, 100A, 110A, 125A, 150A, 175A, 200A, 225A, 250A, 300A, 350A, 400A, 450A, 500A, 600A

Sample P/N: NOS030 for 30A fuse



I.R.: 50kA at 600VAC (Class K5 - 1A to 60A)
 10kA at (Class H - 70A to 600A)
Voltage: 600VAC
Pack Size (box): 10 (1A to 60A)
 5 (70A to 100A)
 1 (110A to 600A)
Holders: Blocks contact sales.
Fuse Classification: Fast Acting (One Time)
Approvals: UL, CE, CE

INDUSTRIAL

Fuse Series	Ampere Ratings	Diagram	Dimensions in MM	
			A	B
NON	125mA-30A	1	50.8	14.2
NON	35A-60A	1	76.3	20.6
NON	70A-100A	2	149.5	26.9
NON	110A-200A	2	181.2	39.7
NON	225A-400A	2	219.4	52.4
NON	450A-600A	2	263.9	65.8
NOS	1A-30A	1	127.1	20.6
NOS	35A-60A	1	139.8	26.9
NOS	70A-100A	2	200.8	34.1
NOS	110A-200A	2	244.8	46.8
NOS	225A-400A	2	295.6	65.8
NOS	450A-600A	2	340.1	79.6

Diagram 1.




Diagram 2.

