These modular bases can be used as stand-alone units or can be ganged together into 3 different configurations as illustrated on page 2. Each fuse base features blown fuse LED indication and 2 slots to store spare fuses. The fuse base also includes a 65 piece sticker set to identify each circuit. All bases include a clear cover. Customers can easily gang the units together by following the included instruction sheet.

Part		$W \times L \times H (mm)$
Number	Description	Dimensions
MFB6SC	6 Way Auto fuse panel, 30A screw terminals & cover	86 x 78 x 4 l
MFB12SC	12 Way Ground panel with screw terminals & cover	$86 \times 57 \times 41$

Voltage: 32V

Max. Cumulative Rating: 100A total. Max. Terminal Rating: 30A (screw). Output Terminals: M4 (5/32") screw. Ground Terminals: M4 (5/32") screw. Input & Ground Studs: M5 (3/16")

Base Colour: Black Cover Colour: Clear

Screws & Lock Washers: Included with screw terminal bases.



Included Sticker Set (refer page 3)



MFB6SC & MFB12SC Ganged together into a single module (fuses not included)



MFB12SC 12 Way Ground Base & Cover



MFB6SC 6 Way Autofuse Base & Cover (fuses not included)




Sample Combination: (I x MFB6SC & I x MFB12SC)



Notes:

- I. Bases can be joined together.
- 2. Fuse base includes a 2 piece clear cover.
- 3. Ground base includes I piece clear cover.
- 4. Sticker set is included with fuse base. No sticker set for ground base.
- 5. Instructions included with each unit for use & assembly.
- 6. LED indication of blown fuses.
- 7. Fuses are not included. We sell fuses to suit in all ratings.
- 8. When combining 2 x 6 way fuse bases to create a 12 way fuse base, the M5 power input stud will supply power to all 12 fuse positions (when assembled correctly using the included instructions).

12 Way Fuse Base Circuit Diagram



RELATED PRODUCTS:





Datasheet: 7008



Email: info@prolecproducts.com Web: www.prolecproducts.com

65 Piece Sticker Set (Included with MFB6SC & MFB6QC Modules)

DECK LIGHTS	DEPTH SOUNDER	ELEC- TRONICS	ENGINE HATCH	OUTLETS	RADAR	RADIO	REFRIG- ERATOR	
FAN	FISH FINDER	FISHING LIGHT	FLOOD LIGHTS	RUNNING LIGHTS	SEARCH LIGHT	SPARE	SPREADER LIGHTS	
FUEL PUMP	FWD CABIN LIGHTS	GPS	HORN	STEAMING LIGHT	STEREO	STROBE LIGHT	TRICOLOR LIGHT	
INSTR. LIGHTS	INSTRU- MENTS	INVERTER	KNOT METER	TRIM TABS	VHF	WASH DOWN	WATER PRESSURE	
LIGHTS	MACERATOR PUMP	MAIN CABIN LIGHTS	NAV LIGHTS	WATER PUMP	WINCHES	WINDLASS	WIPERS	
* 1	12V DC	24V DC	ACCESSORY	- 1				
AERATOR	AFT CABIN LIGHTS	ANCHOR LIGHT	AUTO PILOT	CABIN				
BAIT PUMP	BAITWELL	BATTERY	BATTERY CHARGER	LIGHTS				
BILGE	BILGE PUMP	BLOWER	BOW LIGHT	DC PANEL				
CABIN LIGHTS	CB RADIO	CHART PLOTTER	COMPASS LIGHT	DC SUB PANEL				

DECK LIGHTS DEPTH SOUNDER ELECTRONICS ENGINE HATCH FAN FISH FINDER FISHING LIGHT FLOOD LIGHTS **FUEL PUMP FWD CABIN LIGHTS GPS HORN INSTR. LIGHTS INSTRUMENTS** INVERTER KNOT METER LIGHTS MACERATOR PUMP MAIN CABIN LIGHTS

NAV LIGHTS

Datasheet: 7008

OUTLETS RADAR RADIO REFRIGERATOR **RUNNING LIGHTS** SEARCH LIGHT **SPARE** SPREADER LIGHTS STREAMING LIGHT **STEREO** STROBE LIGHT TRICOLOR LIGHT TRIM TABS VHF WASH DOWN WATER PRESSURE WATER PUMP WINCHES WINDLASS

WIPERS

<EMPTY> 12V DC 24V DC **ACCESSORY AERATOR** AFT CABIN LIGHTS ANCHOR LIGHT **AUTO PILOT BAIT PUMP BAITWELL BATTERY** BATTERY CHARGER **BILGE BILGE PUMP BLOWER BOW LIGHT CABIN LIGHTS** CB RADIO CHART PLOTTER COMPASS LIGHT

<EMPTY>
CABIN
LIGHTS
DC PANEL
DC SUB PANEL