### STUD TYPE JUNCTION BLOCKS - FEED THROUGH

3/8"-16

22 6

## Bussmann

Feed-Through blocks are designed to be used on a firewall or panel.

Part	Body	Amp	Thread	Torque
Number	Colour	Rating	Size M	Stud Max
C2201	Black	200A	5/16-18	11.3
C2202	Red	200A	5/16-18	11.3
C2203	Black	250A	3/8"-16	22.6

250A

Voltage: 1000VAC / 1000VDC Body: Thermoplastic


Rad

Studs: Brass Plating: Tin

C2204

Hardware: Flange nuts included.

Pack Size: 1, 10, 40



Dimensions in MM



### **COMMON BUSBAR MAXIBUS 5/16" STUDS**

#### Features:

- Heavy duty busbar terminal block.
- Insert-molded stainless steel studs.
- One-piece serrated flange nuts ensure correct and secure connection.

 $\frac{Part \, Number}{880118} \qquad \frac{Busbar \, Studs}{4 \times 5/16"-18}$ 

Rating: 250A Voltage: 300VAC / 48VDC

Body: Black

Bus Material: Tin plated copper.
Studs: 5/16"-18 (M8) Stainless steel.
Recommended Terminals: 5/16" or M8 ring.

Hardware: Serrated flange nuts SS.

Mounting Holes: 5mm Pack Size: 1, 10, 50, 100 Dimensionsin MM



# **COMMON BUSBAR POWERBUS 3/8" STUDS**

#### Features:

- Compact heavy duty busbar terminal block.
- Insert-molded stainless steel studs.
- One-piece serrated flange nuts ensure correct and secure connection.

Part Number 880097 Busbar Studs 2 x 3/8"-16

Rating: 600A Voltage: 48V

Body: Glass reinforced polycarbonate


Bus Link: Tin plated copper.


Studs: 3/8"-16 (M10) Stainless steel.

Mounting Holes: #10 or M5 screws

Hardware: Stainless steel nuts & washers included.

Pack Size: 1, 10, 50, 100





Littelfuse

Dimensionsin MM



Email: info@prolecproducts.com.au Web: www.prolecproducts.com.au