


BBS SERIES

Eaton Bussmann
Midget, Fast Acting

Part Number	Ampere Rating
BBS.100	100mA
BBS.200	200mA
BBS.250	250mA
BBS.400	400mA
BBS.500	500mA
BBS.600	600mA
BBS.750	750mA
BBS.800	800mA
BBS001	1A
BBS01.5	1.5A
BBS01.6	1.6A
BBS01.8	1.8A
BBS002	2A
BBS003	3A
BBS004	4A
BBS005	5A
BBS006	6A
BBS007	7A
BBS008	8A
BBS010	10A
BBS012	12A
BBS015	15A
BBS020	20A
BBS025	25A
BBS030	30A



Dimensions in MM

I.R.: 10kA at rated voltage (100mA to 10A)
Voltage (BBS): 600VAC (100mA to 6A)
 250VAC (7A to 10A)
 48VAC (12A to 30A)

Pack Size (box): 10
Holders: Clips (p113)

Approvals: CE (UL) (excludes 12A-30A)

DMM / MMF SERIES

Eaton Bussmann / ETI
Very Fast Acting, Type gR

Part Number	Ampere Rating	I.R.at Voltage	"A" (mm)	
DMM.440	440mA	10kA	34.9	
MMF002	2A	30kA	38.1	NEW
MMF004	4A	30kA	38.1	NEW
MMF006	6A	30kA	38.1	NEW
MMF008	8A	30kA	38.1	NEW
MMF010	10A	30kA	38.1	NEW
DMM011	11A	20kA	38.1	
MMF012	12A	30kA	38.1	NEW
MMF016	16A	30kA	38.1	NEW
MMF020	20A	30kA	38.1	NEW




DMM.440

DMM011

MMF010

Dimensions in MM



Voltage: 1000VAC / 1000VDC

Pack Size (box): 10

Holders: Clips (p113)

Approvals: (440mA & 11A only). UL Recognised E19180
 (2A - 20A). IEC 60269-4, (UL) UL 248-1, UL 248-13

INDUSTRIAL

Looking for Fluke multimeter fuses?

- Fluke 871173 = M205C.630 (see page 15)
- Fluke 892583 = KTK015 (see page 71)
- Fluke 871207 = BBS001 (see above)
- Fluke 943121 = DMM.440 (see above)
- Fluke 203414 = DMM.440 (see above)
- Fluke 803293 = DMM011 (see above)
- Fluke 203406 = DMM011 (see above)

Other multi meter brand spare fuses also available, please contact sales.

