

**KTN-R SERIES 250VAC / 250VDC**

Series	Ampere
Part Number	Range
KTNRxxx	1A to 600A

**Rated:** 1A, 2A, 3A, 4A, 5A, 6A, 8A, 10A, 12A, 15A, 20A, 25A, 30A, 35A, 40A, 45A, 50A, 60A, 70A, 75A, 80A, 90A, 100A, 110A, 125A, 150A, 175A, 200A, 225A, 250A, 300A, 350A, 400A, 450A, 500A, 600A

**Sample P/N:** KTNR005 for 5A fuse



**I.R.:** 200kA at 250VAC, 10kA at 250VDC  
**Voltage:** 250VAC / 250VDC  
**Pack Size (box):** 10 (1A to 60A)  
 5 (70A to 100A)  
 1 (110A to 600A)  
**Holders:** Blocks for fuses up to 30A (p133)  
 Blocks for fuses above 35A contact sales.  
**Fuse Classification:** Fast Acting (Limitron)  
**Approvals:** UL CE

**KTS-R SERIES 600VAC**

Series	Ampere
Part Number	Range
KTSRxxx	1A to 600A

**Rated:** 1A, 2A, 3A, 4A, 5A, 6A, 8A, 10A, 12A, 15A, 20A, 25A, 30A, 35A, 40A, 45A, 50A, 60A, 70A, 75A, 80A, 90A, 100A, 110A, 125A, 150A, 175A, 200A, 225A, 250A, 300A, 350A, 400A, 450A, 500A, 600A

**Sample P/N:** KTSR020 for 20A fuse



**I.R.:** 200kA at 600VAC  
**Voltage:** 600VAC  
**Pack Size (box):** 10 (1A to 60A)  
 1 (70A to 600A)  
**Holders:** Blocks (please contact sales)  
**Fuse Classification:** Fast Acting (Limitron)  
**Approvals:** UL CE

INDUSTRIAL

Dimensions in MM

Fuse	Ampere Ratings	Diagram	A	B
KTNR	1A-30A	1	50.8	14.2
KTNR	35A-60A	1	76.3	20.6
KTNR	70A-100A	2	149.5	26.9
KTNR	110A-200A	2	181.2	39.7
KTNR	225A-400A	2	219.4	52.4
KTNR	450A-600A	2	263.9	65.8
KTSR	1A-30A	1	127.1	20.6
KTSR	35A-60A	1	139.8	26.9
KTSR	70A-100A	2	200.3	25.4
KTSR	110A-200A	2	244.8	38.1
KTSR	225A-400A	2	295.6	50.8
KTSR	450A-600A	2	340.1	63.6

Diagram 1




Diagram 2

