

JJN SERIES 300VAC / 170VDC

Series Part Number Ampere Range
 JJNxxx 1A to 1200A

Ampere Ratings : 1A, 2A, 3A, 6A, 10A, 15A, 20A, 25A, 30A, 35A, 40A, 45A, 50A, 60A, 70A, 80A, 90A, 100A, 110A, 125A, 150A, 175A, 200A, 225A, 250A, 300A, 350A, 400A, 450A, 500A, 600A, 700A, 800A, 1000A, 1200A.

Sample P/N: JJN040 for 40A fuse



I.R.: 200kA at 300VAC
 20kA at 160VDC (15A to 600A)
 100kA at 170VDC (700A to 1200A)

Voltage: 300VAC
 160VDC (15A to 600A)
 170VDC (700A to 1200A)

Characteristic: Very Fast Acting
Holders: Blocks (p135-136)
 Clips (Contact sales).

Approvals:

JJS SERIES 600VAC

Series Part Number Ampere Range
 JJSxxx 1A to 800A

Ampere Ratings : 1A, 2A, 3A, 6A, 10A, 15A, 20A, 25A, 30A, 35A, 40A, 45A, 50A, 60A, 70A, 80A, 90A, 100A, 110A, 125A, 150A, 175A, 200A, 225A, 250A, 300A, 350A, 400A, 450A, 500A, 600A, 800A.

Sample P/N: JJS050 for 50A fuse



I.R.: 200kA at 600VAC

Voltage: 600VAC

Characteristic: Very Fast Acting
Holders: Blocks (p135-136)
 Clips (Contact sales)

Approvals:

Fuse	Ampere Ratings	Diagram	Dimensions in MM					
			A	B	C	D	E	F
JJN	1A - 30A	1	22.4	-	-	10.4	-	-
JJN	35A - 60A	1	22.4	-	-	14.2	-	-
JJN	70A - 100A	3	54.9	39.7	19.1	-	21.4	7.2
JJN	110A - 200A	3	62.0	43.0	22.4	-	21.4	8.7
JJN	225A - 400A	3	69.9	46.8	25.4	-	21.9	10.3
JJN	450A - 600A	3	77.8	51.6	31.8	-	22.4	12.3
JJN	700A - 800A	3	85.9	56.4	44.5	-	23.4	14.3
JJN	1000A	3	101.7	64.3	50.8	-	27.5	15.5
JJN	1200A	3	101.7	64.3	50.8	-	27.5	15.5
JJS	1A - 30A	1	38.1	-	-	14.2	-	-
JJS	35A - 60A	2	39.7	20.6	-	25.4	-	-
JJS	70A - 100A	3	75.0	60.0	19.1	-	41.7	7.1
JJS	110A - 200A	3	82.6	63.6	22.4	-	42.2	8.7
JJS	225A - 400A	3	92.3	69.1	25.4	-	44.0	10.3
JJS	450A - 600A	3	101.2	75.0	31.8	-	45.2	12.3
JJS	700A - 800A	3	110.1	80.6	44.5	-	47.8	14.3

